



## Series 801 "Mighty Mouse" Double-Start ACME Thread

### Series 801 Receptacles With PCB or Solder Cup Contacts



**Series 801 Printed  
Circuit Board Receptacle**

**These receptacles** feature a low profile shell for minimum protrusion inside enclosures. Contacts are non-removable. Connectors are backfilled with epoxy for a watertight seal.

**Two Shell Styles:** jam nut with o-ring for rear panel mounting, or square flange.

**PCB Contacts** feature gold-plated tails for solder termination to rigid or flexible circuits.

**Solder Cup Contacts** are factory-installed and fully sealed with epoxy.

#### HOW TO ORDER

##### Sample Part Number

**801-011**



**-07**

**M**

**7-10**

**P**

**A**

Series	Shell Style	Shell Material / Finish	Shell Size- Insert Arrangement	Contact Type	Shell Key Position
<b>801-011</b> Receptacle	 <p><b>-02</b> Square Flange</p>	<b>C</b> Aluminum / Black Anodize	<b>5-3</b> 3 #23 <b>6-1</b> 1 #16	<b>P</b> Pin, PC Tail	<b>A</b> Normal
		<b>M</b> Aluminum / Electroless Nickel	<b>6-4</b> 4 #23 <b>6-7</b> 7 #23		
		<b>NF</b> Aluminum / Cadmium with Olive Drab Chromate	<b>7-1</b> 1 #12 <b>7-10</b> 10 #23 <b>8-13</b> 13 #23		
		<b>ZN</b> Aluminum / Zinc-Nickel with Olive Drab Chromate	<b>9-4</b> 4 #16 <b>9-19</b> 19 #23 <b>10-26</b> 26 #23		
		<b>ZNU</b> Aluminum / Zinc-Nickel with Black Chromate	<b>13-2</b> 2 #12 <b>13-37</b> 37 #23 <b>16-55</b> 55 #23		
		<b>Z1</b> Stainless Steel / Passivated	<b>17-85</b> 85 #23		
	 <p><b>-07</b> Jam Nut</p>			<b>S</b> Socket, PC Tail	Alternate Key Positions: <b>B</b> <b>C</b> <b>D</b>
				<b>E</b> Pin, Solder Cup	
				<b>F</b> Socket, Solder Cup	

