



## Series 800 “Mighty Mouse” with UN Mating Thread Plug Connector Ordering Information 800-006 Thru 800-009



**Series 800 Plug Connector**

**Compact Size** saves space and weight. Smaller than other Series 800 plugs, these Series 800 plugs are suitable for hostile environments and are watertight when mated.

**Two Shell Styles:** Integral platform for direct shield attachment using **BAND-IT®** termination system, or accessory thread for attaching a strain relief.





**Crimp, Rear Release** contact system, now with #12 and #16 M39029 coaxial or power contacts.

**Two Coupling Nut Styles:** Hex nut or round knurled nut. Either style is available with optional wave spring which helps to prevent the nut from backing off.

### HOW TO ORDER

Sample Part Number

**800-006      -06      M      7-10      P      Z**

Series	Shell Style	Shell Material / Finish	Shell Size- Insert Arrangement					Contact Type	Shell Key Position
 <b>800-006</b> Hex Plug with Banding Platform   <b>800-007</b> Hex Plug with Accessory Thread   <b>800-008</b> Knurled Round Plug with Band Platform   <b>800-009</b> Knurled Round Plug with Accessory Thread	<b>-06</b> Standard Coupling Nut	<b>C</b> Aluminum / Black Anodize (Non-Conductive) RoHS Compliant	No. of Contacts					<p><b>Connector supplied with contacts</b></p> <p><b>P</b> Pin</p> <p><b>S</b> Socket</p> <p><b>Connector supplied without contacts</b></p> <p><b>A</b> Pin</p> <p><b>B</b> Socket Connector</p> <p>Connectors with contacts are supplied with signal and/or power crimp contacts. These contacts are not installed.</p> <p>Coaxial contacts and non-standard signal contacts are ordered separately.</p>	<b>N</b> Normal
	<b>-16</b> Coupling Nut with Anti-Decoupling Wave Spring	<b>M</b> Aluminum / Electroless Nickel RoHS Compliant	Arr.	#23	#20	#16	#12		<b>X</b> Pos. X
	<b>5-3</b>		3						<b>Y</b> Pos. Y
	<b>6-1</b>				1				<b>Z</b> Pos. Z
	<b>6-4</b>		4						
	<b>6-7</b>		7						
	<b>7-1</b>					1			
	<b>7-10</b>		10						
	<b>8-2</b>				2				
	<b>8-13</b>		13						
	<b>8-200</b>		4	2					
	<b>9-4</b>				4				
	<b>9-19</b>		19						
	<b>9-200</b>		4		2				
	<b>9-201</b>		8	2					
	<b>10-5</b>				5				
	<b>10-26</b>		26						
	<b>10-200</b>		12			1			
	<b>10-201</b>		4			2			
<b>10-202</b>		8		2					
<b>12-2</b>					2				
<b>12-3</b>					3				
<b>12-7</b>					7				
<b>12-37</b>		37							
<b>12-200</b>		6			2				
<b>12-201</b>		10			2				

